

# Neets EasyConnect

Complete AV Connectivity and Control for Your Tabletop

Neets EasyConnect Power



Neets EasyConnect Control



## HIGHLIGHTS

### BOTH UNITS:

- All-in-one tabletop solution
- No cables on the floor  
AV cables (1.7 m) pull out and retract easily for storage
- Standard version connects HDMI, 3.5 mm audio mini-jack, VGA, network cable (RJ45), USB-A
- Sliding cover with cable pass-through

### EASYCONNECT POWER:

- Two AC power sockets:  
EU, Universal or  
DK power connector

### EASYCONNECT CONTROL:

- Direct access to AV control functions  
Neets Control - Echo or  
Neets Control - SieRRa integration
- One AC power connector:  
EU, Universal or DK power connector
- Direct-out 12V power supply

## CONNECTION AND CONTROL, RIGHT WHERE YOU ARE

Neets EasyConnect solves one of the most common and frustrating problems encountered in AV presentations. When a guest presenter wants to connect a laptop computer, all too often the proper cables cannot be found, or they are too short, or the connection point is hidden away in a floor pocket or wall panel.

Neets EasyConnect is the obvious solution. All necessary connections are readily accessible, right on the tabletop or lectern, inside this durable metal enclosure. The standard version accommodates all five typical connections for laptop computers and most tablet-type mobile devices. A sixth cable (optional) can be included to accommodate, for example, a DVI connector, an XLR microphone, ¼" audio jack or RCA jack for composite video. The integrated AC power receptacle eliminates the need to find extension cords for connecting to distant wall outlets.

The EasyConnect system is sold as a package - either as EasyConnect Control - Echo or as EasyConnect Control - SieRRa integration of a Neets AV system control module. With integrated control, starting a presentation is quick and frustration-free. Simply plug in the required cables, press the corresponding control buttons, and your presentation is underway in a matter of seconds!

The EasyConnect Power unit has 2 power supply sockets, but the same look and size as the EasyConnect Control, and is mainly a complimentary addition to the EasyConnect Control, adding more power sockets and cables but no control functions to the handy tabletop solution.

Cables are terminated at both ends for easy disconnection and re-connection, allowing use in lecterns that occasionally must be relocated or removed for storage.

# Neets

## Neets EasyConnect Power & Neets EasyConnect Control

### Complete AV Connectivity and Control for Your Tabletop



3.5 mm audio,  
HDMI,  
USB-A,  
VGA,  
Cat-5 type (RJ45)  
Cat-5 type (RJ45)



EU "schuko"  
power socket



Universal  
power socket



DK  
power socket



## TECHNICAL SPECIFICATIONS

### BOTH UNITS:

#### ENCLOSURE TYPE:

Metal (steel box with cast aluminum top and lid)

#### DEFAULT CABLES:

HDMI, VGA, USB-A,  
3.5 mm audio,  
Cat-5 type (RJ45)

#### AC POWER CONNECTOR:

EU, Universal or DK  
power connector

#### DIMENSIONS:

Recessed box:  
Width: 218.4 mm  
Depth: 89.5 mm  
Height: 103 mm  
Top plate:  
Width: 252 mm  
Depth: 135.5 mm

#### WEIGHT:

2.15 kg

#### NEETS EASYCONNECT POWER:

Two EU, Universal or  
DK power socket

### NEETS CONTROL - ECHO: COMMUNICATION PORTS:

1 X RS-232 (TX and RX)  
Baud: 1200 – 115200  
Data Bit: 7/8  
Parity: None, Even, Odd  
Stop Bit: 1/1.5/2  
1 x RS-232 or IR (TX only)  
RS-232  
Baud: 1200 – 115200  
Parity: None, even, odd  
Stop Bit: 1/1.5/2

#### IR:

Transmit  
381 Hz – 500 kHz  
Devices: 2

#### 3 X INPUT/OUTPUT:

##### INPUT:

Sense Low: <1 VDC  
Sense High: >4 VDC

##### OUTPUT:

Type: Open drain  
Max Voltage: 24 VDC  
Max Current: 0.5 A

### NEETS EXPANSION BUS (NEB)

12 V (0.3 A) output  
See neets.dk for NEB info

#### CONFORMITY:

Approval: CE  
EN 55022, EN 55024

### NEETS CONTROL - SIERRA: COMMUNICATION PORTS:

1 X RS-232 (TX and RX)  
Baud: 1200 – 115200  
Data Bit: 7/8  
Parity: None, even, odd  
Stop Bit: 1/1.5/2  
2 x RS-232 or IR (TX only both)  
RS-232  
Baud: 1200 – 115200  
Parity: None, Even, Odd  
Stop Bit: 1/1.5/2

#### IR:

Transmit  
381 Hz – 500 kHz  
Devices: 4

#### LAN:

Speed: 10/100 Mbit  
auto-detect  
Devices: 5

#### 3 X INPUT/OUTPUT:

##### INPUT:

Sense Low: <1 VDC  
Sense High: >4 VDC

##### OUTPUT:

Type: Open drain  
Max Voltage: 24 VDC  
Max Current: 0.5 A

### NEETS EXPANSION BUS (NEB):

12 V (0.3 A) output  
See neets.dk for NEB info

#### CONFORMITY:

Approval: CE  
EN 55022, EN 55024

### PRODUCT ITEM NUMBERS:

305-0200 EasyConnect - Echo EU,  
includes a set of default cables,  
Neets Control - Echo  
and EU power socket.

305-0201 EasyConnect - SieRRa EU,  
includes a set of default cables, Neets  
Control - Echo  
and EU power socket.

305-0205 EasyConnect - Echo EU,  
includes a set of default cables,  
Neets Control - Echo  
and universal power socket.

305-0206 EasyConnect - SieRRa EU,  
includes a set of default cables, Neets  
Control - Echo  
and universal power socket.

305-0202 EasyConnect - Echo DK,  
includes a set of default cables, Neets  
Control - Echo  
and DK power socket.

305-0203 EasyConnect - SieRRa DK,  
includes a set of default cables, Neets  
Control - SieRRa and DK power socket.

305-0250 EasyConnect Power EU,  
includes a set of default cables and  
two EU power sockets.

305-0251 EasyConnect Power DK,  
includes a set of default cables and  
two DK power sockets.

305-0252 EasyConnect Power Uni,  
includes a set of default cables and  
two Uni power sockets.

# Neets

Phone: +45 75 666 099 • E-mail: sales@neets.dk • www.neets.dk