## KanexPro

1405 Pioneer St., Brea, CA 92821 888.975.1368 | info@kanexpro.com

### Component with Audio to HDMI Converter

Convert component video and analog audio to HDMI

#### **MPN: RGBRLHD**



#### **FEATURES**

- Convert YPbPr (Component-video) and audio source to an HDMI display
- Supports data rates to 6.75Gbps
- HDMI output resolutions up to 1080p (1920x1080@60Hz)
- Supports analog video input to 1080p & UXGA (1600x1200) with 10-bit DAC
- Encodes analog audio signal to HDMI
- Compact size
- 5VDC external power supply included

#### SPECIFICATIONS

Input: Component(YPbPr+R/L) x1 Output: HDMI x1 Audio Input Connector: Toslink & Digital Audio Video Amplifier Bandwidth: 6.75Gbps Vertical Frequency Range: 50/60Hz Color Depth: 8-bit per channel Resolutions (HDTV): 480p/576p/720p/1080i/1080p Power Supply: 5V DC@2A Power Consumption: 5W

# Source Display VCR/DVD RGB Component Video HD TV RCA Audio HD MI Image: Component Video HD TV

#### ABOUT KANEXPRO

KanexPro carries a broad selection of A/V connectivity products by leveraging the core strength in professional systems enabling you to broadcast, convert, extend, split, or multiply HD signal transmissions; simply and cost-effectively. KanexPro is a trademark. HDMI, the HDMI logo, and High-Definition Multimedia Interface are trademarks or registered trademarks of HDMI Licensing, LLC in the United States and/or other countries. All other product or service names are the property of their respective owners.

#### The KanexPro component audio-video converter to HDMI

is a classic fit for older, analog devices that need seamless integration for today's home theater environments. It connects your component video sources such as VCR, DVD player and high-resolution cameras to HDMI compliant displays and projectors.

The converter takes the R+L audio and encodes it to the HDMI signal for high-resolution video and audio playback. Ideal and cost-effective for legacy hometheater equipment that need the transition to HDMI displays.