

SQ-5100 IrDA

UHF 100-freq wireless handheld transmitter


GENERAL FEATURES

- Clear and intuitive LCD display for easy operation and quick set-up.
- Patented IrDA technology for 2-way data transfer between transmitter and receiver.
- Slide switch to lock transmitter on stand-by mode.
- 3-step power control to switch between ON-MUTE-OFF status.
- Various microphone modules for versatile, professional live sound.
- Operating time up to 16 hours with 2 AA batteries.
- Matched battery charger: HC-92.
(Optional, use with rechargeable batteries only.)
- Sturdy ABS housing.

SPECIFICATIONS

Model	SQ-5100 IrDA
Frequency Range	UHF 500-900 MHz
Switching Bandwidth	25 MHz
Switchable Frequency	100
2-way synchronization	Yes
Spurious Emission	> 60 dB below carrier
Dynamic Range	> 110 dB
Display Screen	LCD
T.H.D	< 0.5%
Peak Deviation	±40KHz
Antenna	Built-in
Battery Type	AA*2
Operating Life (Alkaline)	16 hours
Charging Function	Yes
Battery charger	HC-92
Microphone Capsule	Dynamic/condenser type
Dimension (mm)	Ø53*256
Weight (g)	230

Remark: The above specifications are subject to change without prior notice.
** The output power may vary from country to country.



Slide switch to lock transmitter on stand-by mode.